This Page Is Inserted by IFW Operations
and is not a part of the Official Record

BEST AVAILABLE IMAGES

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images may include (but are not limited to):

- BLACK BORDERS
- TEXT CUT OFF AT TOP, BOTTOM OR SIDES
- FADED TEXT
- ILLEGIBLE TEXT
- SKEWED/SLANTED IMAGES
- COLORED PHOTOS
- BLACK OR VERY BLACK AND WHITE DARK PHOTOS
- GRAY SCALE DOCUMENTS

IMAGES ARE BEST AVAILABLE COPY.

As rescanning documents *will not* correct images, please do not report the images to the Image Problems Mailbox.

SIMO MÄENPÄÄ
02-
P. 2449425

Second Edition

Field and Wave Electromagnetics

David K. Cheng
Life Fellow, I.E.E.E.;
Fellow, I.E.E.; C. Eng.

ADDISON-WESLEY PUBLISHING COMPANY
Reading, Massachusetts · Menlo Park, California · New York
Don Mills, Ontario · Wokingham, England · Amsterdam · Bonn
Sydney · Singapore · Tokyo · Madrid · San Juan

WORLD STUDENT SERIES EDITION

This book is in the Addison-Wesley Series in Electrical Engineering

Barbara Rifkind: *Sponsoring Editor*
Karen Myer: *Production Supervisor*
Hugh Crawford: *Manufacturing Supervisor*
Joseph K. Vetere: *Technical Art Consultant*
Catherine Dorin: *Interior Designer*
Marshall Henrichs: *Cover Designer*
Patsy DuMoulin: *Production Coordinator*

Copyright © 1989 by Addison-Wesley Publishing Company, Inc.

All rights reserved. No part of this publication may be reproduced, stored in a retrieval system, or transmitted, in any form or by any means, electronic, mechanical, photocopying, recording, or otherwise, without the prior written permission of the publisher. Printed in the United States of America. Published simultaneously in Canada.

ISBN 0-201-12810-1

45678-DO-939291

Fourth Printing, January 1991.

Preface

The many books on introductory electromagnetics can be roughly divided into two main groups. The first group takes the traditional development: starting with the experimental laws, generalizing them in steps, and finally synthesizing them in the form of Maxwell's equations. This is an inductive approach. The second group takes the axiomatic development: starting with Maxwell's equations, identifying each with the appropriate experimental law, and specializing the general equations to static and time-varying situations for analysis. This is a deductive approach. A few books begin with a treatment of the special theory of relativity and develop all of electromagnetic theory from Coulomb's law of force; but this approach requires the discussion and understanding of the special theory of relativity first and is perhaps best suited for a course at an advanced level.

Proponents of the traditional development argue that it is the way electromagnetic theory was unraveled historically (from special experimental laws to Maxwell's equations), and that it is easier for the students to follow than the other methods. I feel, however, that the way a body of knowledge was unraveled is not necessarily the best way to teach the subject to students. The topics tend to be fragmented and cannot take full advantage of the conciseness of vector calculus. Students are puzzled at, and often form a mental block to, the subsequent introduction of gradient, divergence, and curl operations. As a process for formulating an electromagnetic model, this approach lacks cohesiveness and elegance.

The axiomatic development usually begins with the set of four Maxwell's equations, either in differential or in integral form, as fundamental postulates. These are equations of considerable complexity and are difficult to master. They are likely to cause consternation and resistance in students who are hit with all of them at the beginning of a book. Alert students will wonder about the meaning of the field vectors and about the necessity and sufficiency of these general equations. At the initial stage students tend to be confused about the concepts of the electromagnetic model, and they are not yet comfortable with the associated mathematical manipulations. In any case, the general Maxwell's equations are soon simplified to apply to static fields,

Contents

1 The Electromagnetic Model 1

1-1 Introduction 1
1-2 The Electromagnetic Model 3
1-3 SI Units and Universal Constants 8
Review Questions 10

2 Vector Analysis 11

2-1 Introduction 11
2-2 Vector Addition and Subtraction 12
2-3 Products of Vectors 14
2-3.1 Scalar or Dot Product 14
2-3.2 Vector or Cross Product 16
2-3.3 Product of Three Vectors 18
2-4 Orthogonal Coordinate Systems 20
2-4.1 Cartesian Coordinates 23
2-4.2 Cylindrical Coordinates 27
2-4.3 Spherical Coordinates 31
2-5 Integrals Containing Vector Functions 37
2-6 Gradient of a Scalar Field 42
2-7 Divergence of a Vector Field 46
2-8 Divergence Theorem 50
2-9 Curl of a Vector Field 54
2-10 Stokes's Theorem 58

2–11 Two Null Identities 61
2–11.1 Identity I 61
2–11.2 Identity II 62
2–12 Helmholtz's Theorem 63
Review Questions 66
Problems 67

3 Static Electric Fields 72

3–1 Introduction 72
3–2 Fundamental Postulates of Electrostatics in Free Space 74
3–3 Coulomb's Law 77
3–3.1 Electric Field Due to a System of Discrete Charges 82
3–3.2 Electric Field Due to a Continuous Distribution of Charge 84
3–4 Gauss's Law and Applications 87
3–5 Electric Potential 92
3–5.1 Electric Potential Due to a Charge Distribution 94
3–6 Conductors in Static Electric Field 100
3–7 Dielectrics in Static Electric Field 105
3–7.1 Equivalent Charge Distributions of Polarized Dielectrics 106
3–8 Electric Flux Density and Dielectric Constant 109
3–8.1 Dielectric Strength 114
3–9 Boundary Conditions for Electrostatic Fields 116
3–10 Capacitance and Capacitors 121
3–10.1 Series and Parallel Connections of Capacitors 126
3–10.2 Capacitances in Multiconductor Systems 129
3–10.3 Electrostatic Shielding 132
3–11 Electrostatic Energy and Forces 133
3–11.1 Electrostatic Energy in Terms of Field Quantities 137
3–11.2 Electrostatic Forces 140
Review Questions 143
Problems 145

4 Solution of Electrostatic Problems 152

4–1 Introduction 152
4–2 Poisson's and Laplace's Equations 152
4–3 Uniqueness of Electrostatic Solutions 157

4–4 Method of Images 159
4–4.1 Point Charge and Conducting Planes 161
4–4.2 Line Charge and Parallel Conducting Cylinder 162
4–4.3 Point Charge and Conducting Sphere 170
4–4.4 Charged Sphere and Grounded Plane 172
4–5 Boundary-Value Problems in Cartesian Coordinates 174
4–6 Boundary-Value Problems in Cylindrical Coordinates 183
4–7 Boundary-Value Problems in Spherical Coordinates 188
Review Questions 192
Problems 193

5 Steady Electric Currents 198

5–1 Introduction 198
5–2 Current Density and Ohm's Law 199
5–3 Electromotive Force and Kirchhoff's Voltage Law 205
5–4 Equation of Continuity and Kirchhoff's Current Law 208
5–5 Power Dissipation and Joule's Law 210
5–6 Boundary Conditions for Current Density 211
5–7 Resistance Calculations 215
Review Questions 219
Problems 220

6 Static Magnetic Fields 225

6–1 Introduction 225
6–2 Fundamental Postulates of Magnetostatics in Free Space 226
6–3 Vector Magnetic Potential 232
6–4 The Biot-Savart Law and Applications 234
6–5 The Magnetic Dipole 239
6–5.1 Scalar Magnetic Potential 242
6–6 Magnetization and Equivalent Current Densities 243
6–6.1 Equivalent Magnetization Charge Densities 247
6–7 Magnetic Field Intensity and Relative Permeability 249
6–8 Magnetic Circuits 251
6–9 Behavior of Magnetic Materials. 257
6–10 Boundary Conditions for Magnetostatic Fields 262
6–11 Inductances and Inductors 266

6–12 Magnetic Energy 277
6–12.1 Magnetic Energy in Terms of Field Quantities 279
6–13 Magnetic Forces and Torques 281
6–13.1 Hall Effect 282
6–13.2 Forces and Torques on Current-Carrying Conductors 283
6–13.3 Forces and Torques in Terms of Stored Magnetic Energy 289
6–13.4 Forces and Torques in Terms of Mutual Inductance 292
Review Questions 294
Problems 296

7 Time-Varying Fields and Maxwell's Equations 307

7–1 Introduction 307
7–2 Faraday's Law of Electromagnetic Induction 308
7–2.1 A Stationary Circuit in a Time-Varying Magnetic Field 309
7–2.2 Transformers 310
7–2.3 A Moving Conductor in a Static Magnetic Field 314
7–2.4 A Moving Circuit in a Time-Varying Magnetic Field 317
7–3 Maxwell's Equations 321
7–3.1 Integral Form of Maxwell's Equations 323
7–4 Potential Functions 326
7–5 Electromagnetic Boundary Conditions 329
7–5.1 Interface between Two Lossless Linear Media 330
7–5.2 Interface between a Dielectric and a Perfect Conductor 331
7–6 Wave Equations and Their Solutions 332
7–6.1 Solution of Wave Equations for Potentials 333
7–6.2 Source-Free Wave Equations 334
7–7 Time-Harmonic Fields 335
7–7.1 The Use of Phasors—A Review 336
7–7.2 Time-Harmonic Electromagnetics 338
7–7.3 Source-Free Fields in Simple Media 340
7–7.4 The Electromagnetic Spectrum 343
Review Questions 346
Problems 347

8 Plane Electromagnetic Waves 354

8–1 Introduction 354
8–2 Plane Waves in Lossless Media 355
8–2.1 Doppler Effect 360

DEC-04-2003 12:15 BLACK LOWE GRAHAM 2063813301 P.18

8–2.2 Transverse Electromagnetic Waves 361
8–2.3 Polarization of Plane Waves 364

8–3 Plane Waves in Lossy Media 367
8–3.1 Low-Loss Dielectrics 368
8–3.2 Good Conductors 369
8–3.3 Ionized Gases 373

8–4 Group Velocity 375

8–5 Flow of Electromagnetic Power and the Poynting Vector 379
8–5.1 Instantaneous and Average Power Densities 382

8–6 Normal Incidence at a Plane Conducting Boundary 386

8–7 Oblique Incidence at a Plane Conducting Boundary 390
8–7.1 Perpendicular Polarization 390
8–7.2 Parallel Polarization 395

8–8 Normal Incidence at a Plane Dielectric Boundary 397

8–9 Normal Incidence at Multiple Dielectric Interfaces 401
8–9.1 Wave Impedance of the Total Field 403
8–9.2 Impedance Transformation with Multiple Dielectrics 404

8–10 Oblique Incidence at a Plane Dielectric Boundary 406
8–10.1 Total Reflection 408
8–10.2 Perpendicular Polarization 411
8–10.3 Parallel Polarization 414

Review Questions 417

Problems 419

9 Theory and Applications of Transmission Lines 427

9–1 Introduction 427

9–2 Transverse Electromagnetic Wave along a Parallel-Plate Transmission Line 429
9–2.1 Lossy Parallel-Plate Transmission Lines 433
9–2.2 Microstrip Lines 435

9–3 General Transmission-Line Equations 437
9–3.1 Wave Characteristics on an Infinite Transmission Line 439
9–3.2 Transmission-Line Parameters 444
9–3.3 Attenuation Constant from Power Relations 447

9–4 Wave Characteristics on Finite Transmission Lines 449
9–4.1 Transmission Lines as Circuit Elements 454
9–4.2 Lines with Resistive Termination 460
9–4.3 Lines with Arbitrary Termination 465
9–4.4 Transmission-Line Circuits 467

9–5 Transients on Transmission Lines 471
9–5.1 Reflection Diagrams 474

9-5.2 Pulse Excitation 478
9-5.3 Initially Charged Line 480
9-5.4 Line with Reactive Load 482

9-6 The Smith Chart 485
9-6.1 Smith-Chart Calculations for Lossy Lines 495

9-7 Transmission-Line Impedance Matching 497
9-7.1 Impedance Matching by Quarter-Wave Transformer 497
9-7.2 Single-Stub Matching 501
9-7.3 Double-Stub Matching 505

Review Questions 509
Problems 512

10 Waveguides and Cavity Resonators 520

10-1 Introduction 520
10-2 General Wave Behaviors along Uniform Guiding Structures 521
10-2.1 Transverse Electromagnetic Waves 524
10-2.2 Transverse Magnetic Waves 525
10-2.3 Transverse Electric Waves 529

10-3 Parallel-Plate Waveguide 534
10-3.1 TM Waves between Parallel Plates 534
10-3.2 TE Waves between Parallel Plates 539
10-3.3 Energy-Transport Velocity 541
10-3.4 Attenuation in Parallel-Plate Waveguides 543

10-4 Rectangular Waveguides 547
10-4.1 TM Waves in Rectangular Waveguides 547
10-4.2 TE Waves in Rectangular Waveguides 551
10-4.3 Attenuation in Rectangular Waveguides 555
10-4.4 Discontinuities in Rectangular Waveguides 559

10-5 Circular Waveguides 562
10-5.1 Bessel's Differential Equation and Bessel Functions 563
10-5.2 TM Waves in Circular Waveguides 567
10-5.3 TE Waves in Circular Waveguides 569

10-6 Dielectric Waveguides 572
10-6.1 TM Waves along a Dielectric Slab 572
10-6.2 TE Waves along a Dielectric Slab 576
10-6.3 Additional Comments on Dielectric Waveguides 579

10-7 Cavity Resonators 582
10-7.1 Rectangular Cavity Resonators 582
10-7.2 Quality Factor of Cavity Resonator 586
10-7.3 Circular Cavity Resonator 589

Review Questions 592
Problems 594

DEC-04-2003 12:15 BLACK LOWE GRAHAM 2063813301 P.20

11 Antennas and Radiating Systems 600

11–1 Introduction 600
11–2 Radiation Fields of Elemental Dipoles 602
11–2.1 The Elemental Electric Dipole 602
11–2.2 The Elemental Magnetic Dipole 605
11–3 Antenna Patterns and Antenna Parameters 607
11–4 Thin Linear Antennas 614
11–4.1 The Half-Wave Dipole 617
11–4.2 Effective Antenna Length 619
11–5 Antenna Arrays 621
11–5.1 Two-Element Arrays 622
11–5.2 General Uniform Linear Arrays 625
11–6 Receiving Antennas 631
11–6.1 Internal Impedance and Directional Pattern 632
11–6.2 Effective Area 634
11–6.3 Backscatter Cross Section 637
11–7 Transmit-Receive Systems 639
11–7.1 Friis Transmission Formula and Radar Equation 639
11–7.2 Wave Propagation near Earth's Surface 642
11–8 Some Other Antenna Types 643
11–8.1 Traveling-Wave Antennas 643
11–8.2 Helical Antennas 645
11–8.3 Yagi-Uda Antenna 648
11–8.4 Broadband Antennas 650
11–9 Aperture Radiators 655
References 661
Review Questions 662
Problems 664

Appendixes

A Symbols and Units 671

A–1 Fundamental SI (Rationalized MKSA) Units 671
A–2 Derived Quantities 671
A–3 Multiples and Submultiples of Units 673

B Some Useful Material Constants 674

B–1 Constants of Free Space 674
B–2 Physical Constants of Electron and Proton 674

Equation (6–23) enables us to find the vector magnetic potential **A** from the volume current density **J**. The magnetic flux density **B** can then be obtained from $\nabla \times \mathbf{A}$ by differentiation, in a way similar to that of obtaining the static electric field **E** from $-\nabla V$.

Vector potential **A** relates to the magnetic flux Φ through a given area S that is bounded by contour C in a simple way:

$$\Phi = \int_S \mathbf{B} \cdot d\mathbf{s} \tag{6–24}$$

The SI unit for magnetic flux is weber (Wb), which is equivalent to tesla-square meter ($\mathrm{T \cdot m^2}$). Using Eq. (6–15) and Stokes's theorem, we have

$$\Phi = \int_S (\nabla \times \mathbf{A}) \cdot d\mathbf{s} = \oint_C \mathbf{A} \cdot d\boldsymbol{\ell} \quad \text{(Wb)}. \tag{6–25}$$

Thus, vector magnetic potential **A** does have physical significance in that its line integral around any closed path equals the total magnetic flux passing through the area enclosed by the path.

6–4 The Biot-Savart Law and Applications

In many applications we are interested in determining the magnetic field due to a current-carrying circuit. For a thin wire with cross-sectional area S, dv' equals $S\,d\ell'$, and the current flow is entirely along the wire. We have

$$\mathbf{J}\,dv' = \mathbf{J}S\,d\ell' = I\,d\ell', \tag{6–26}$$

and Eq. (6–23) becomes

$$\boxed{\mathbf{A} = \frac{\mu_0 I}{4\pi} \oint_C \frac{d\ell'}{R} \quad \text{(Wb/m)}} \tag{6–27}$$

where a circle has been put on the integral sign because the current I must flow in a closed path,† which is designated C'. The magnetic flux density is then

$$\mathbf{B} = \nabla \times \mathbf{A} = \nabla \times \left[\frac{\mu_0 I}{4\pi} \oint_C \frac{d\ell'}{R}\right] = \frac{\mu_0 I}{4\pi} \oint_C \nabla \times \left(\frac{d\ell'}{R}\right). \tag{6–28}$$

† We are now dealing with direct (non-time-varying) currents that give rise to steady magnetic fields. Circuits containing time-varying sources may send time-varying currents along an open wire and deposit charges at its ends. Antennas are examples.

It is very important to note in Eq. (6–28) that the *unprimed* curl operation implies differentiations with respect to the space coordinates of the *field point*, and that the integral operation is with respect to the *primed source coordinates*. The integrand in Eq. (6–28) can be expanded into two terms by using the following identity (see Problem P.2–37):

$$\nabla \times (f\mathbf{G}) = f\nabla \times \mathbf{G} + (\nabla f) \times \mathbf{G}. \tag{6–29}$$

We have, with $f = 1/R$ and $\mathbf{G} = d\ell'$,

$$\mathbf{B} = \frac{\mu_0 I}{4\pi} \oint_{C'} \left[\frac{1}{R} \nabla \times d\ell' + \left(\nabla \frac{1}{R} \right) \times d\ell' \right]. \tag{6–30}$$

Now, since the unprimed and primed coordinates are independent, $\nabla \times d\ell'$ equals 0, and the first term on the right side of Eq. (6–30) vanishes. The distance R is measured from $d\ell'$ at (x', y', z') to the field point at (x, y, z). Thus we have

$$\begin{aligned} \frac{1}{R} &= [(x - x')^2 + (y - y')^2 + (z - z')^2]^{-1/2}; \\ \nabla\left(\frac{1}{R}\right) &= \mathbf{a}_x \frac{\partial}{\partial x}\left(\frac{1}{R}\right) + \mathbf{a}_y \frac{\partial}{\partial y}\left(\frac{1}{R}\right) + \mathbf{a}_z \frac{\partial}{\partial z}\left(\frac{1}{R}\right) \\ &= -\frac{\mathbf{a}_x(x - x') + \mathbf{a}_y(y - y') + \mathbf{a}_z(z - z')}{[(x - x')^2 + (y - y')^2 + (z - z')^2]^{3/2}} \\ &= -\frac{\mathbf{R}}{R^3} = -\mathbf{a}_R \frac{1}{R^2}, \end{aligned} \tag{6–31}$$

where $\mathbf{a}_R$ is the unit vector directed *from the source point to the field point*. Substituting Eq. (6–31) in Eq. (6–30), we get

$$\boxed{\mathbf{B} = \frac{\mu_0 I}{4\pi} \oint_{C'} \frac{d\ell' \times \mathbf{a}_R}{R^2} \quad \text{(T)}} \tag{6–32}$$

Equation (6–32) is known as *Biot-Savart law*. It is a formula for determining $\mathbf{B}$ caused by a current I in a closed path C' and is obtained by taking the curl of $\mathbf{A}$ in Eq. (6–27). Sometimes it is convenient to write Eq. (6–32) in two steps:

$$\boxed{\mathbf{B} = \oint_{C'} d\mathbf{B} \quad \text{(T)}} \tag{6–33a}$$

with

$$\boxed{d\mathbf{B} = \frac{\mu_0 I}{4\pi} \left(\frac{d\ell' \times \mathbf{a}_R}{R^2} \right) \quad \text{(T)}} \tag{6–33b}$$

DEC-04-2003 12:17 BLACK LOWE GRAHAM 2063813301 P.23



FIGURE 6–5
A current-carrying straight wire (Example 6–4).

which is the magnetic flux density due to a current element $I\,d\ell'$. An alternative and sometimes more convenient form for Eq. (6–33b) is

$$d\mathbf{B} = \frac{\mu_0 I}{4\pi}\left(\frac{d\ell' \times \mathbf{R}}{R^3}\right) \quad (\mathrm{T}) \tag{6–33c}$$

Comparison of Eq. (6–32) with Eq. (6–10) will reveal that Biot-Savart law is, in general, more difficult to apply than Ampère's circuital law. However, Ampère's circuital law is not useful for determining $\mathbf{B}$ from I in a circuit if a closed path cannot be found over which $\mathbf{B}$ has a constant magnitude.

EXAMPLE 6–4 A direct current I flows in a straight wire of length $2L$. Find the magnetic flux density $\mathbf{B}$ at a point located at a distance r from the wire in the bisecting plane: (a) by determining the vector magnetic potential $\mathbf{A}$ first, and (b) by applying Biot-Savart law.

Solution Currents exist only in closed circuits. Hence the wire in the present problem must be a part of a current-carrying loop with several straight sides. Since we do not know the rest of the circuit, Ampère's circuital law cannot be used to advantage. Refer to Fig. 6–5. The current-carrying line segment is aligned with the z-axis. A typical element on the wire is

$$d\ell' = \mathbf{a}_z\, dz'.$$

The cylindrical coordinates of the field point P are $(r, 0, 0)$.

a) *By finding* $\mathbf{B}$ *from* $\nabla \times \mathbf{A}$. Substituting $R = \sqrt{z'^2 + r^2}$ into Eq. (6–27), we have

$$\begin{aligned}\mathbf{A} &= \mathbf{a}_z \frac{\mu_0 I}{4\pi}\int_{-L}^{L} \frac{dz'}{\sqrt{z'^2 + r^2}} \\ &= \mathbf{a}_z \frac{\mu_0 I}{4\pi}\left[\ln\left(z' + \sqrt{z'^2 + r^2}\right)\right]\Big|_{-L}^{L} \\ &= \mathbf{a}_z \frac{\mu_0 I}{4\pi}\ln\frac{\sqrt{L^2 + r^2} + L}{\sqrt{L^2 + r^2} - L}.\end{aligned} \tag{6–34}$$

KIRJALLISUUS

[1] Rautio, K., Tunturi T-road juoksumaton ohjelmistosuunnitelma. Mariachi Oy, Turku, 2000.

[2] Peltonen, P., Toteutusmäärittely TIE käyttöliittymäelektroniikka (IUE). Mariachi Oy, Turku, 1998.

[3] Lamberg, P., T-road schema. Mariachi Oy, Turku, 2000.

[4] Rautio, K., Tunturi T-road juoksumatto ala- ja yläkortin välinen viestintä. Mariachi Oy, Turku, 2000.

[5] Rautio, K., TIE IUE ohjelmiston toteutus. Mariachi Oy, Turku, 1998.

[6] Edwards, S., The Heart Rate Monitor Book. Fleet Feet Press, Sacramento, 1993.

[7] Polar OEM handbook Version 1.3. Polar Electro Oy, Kempele, 2000.

[8] Polar Electro, Operational and technical description T31 transmitter. Polar Electro Oy, Kempele, 2000.

[9] Polar Electro, Operational and technical description T41 transmitter. Polar Electro Oy, Kempele, 2000.

[10] Polar Electro, PCBA receiver operational and technical description. Polar Electro Oy, Kempele, 2000.

[11] Cheng, D., Field and Wave Electromagnetics. Addison-Wesley Publishing Company, New York, 1991.

[12] Voipio, E., Sähkö- ja magneettikentät. Otakustantamo, Helsinki, 1976.

[13] Millman, J. ja Grabel, A., Microelectronics, 2nd edition. McGraw-Hill Book Co, Singapore, 1987.

[14] http://pdf.toshiba.com/taec/components/Datasheet/C807.pdf www-dokumentti, luettu 10.7.2001.